

08-23-00

A

PATENT APPLICATION

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

Attorney Docket No. 12547US02

PATENT APPLICATION TRANSMITTAL

Box Patent Application
Assistant Commissioner for Patents
Washington, D.C. 20231

Sir:

Transmitted herewith for filing is the patent application of

Inventor(s): Shanna D. Knights, David P. Wilkinson, Stephen A. Campbell, Jarad L. Taylor,
John M. Gascoyne and Thomas R. Ralph

Title: SOLID POLYMER FUEL CELL WITH IMPROVED VOLTAGE REVERSAL
TOLERANCE

1. Type of Application

This new application is for a:

☒ utility patent.

☐ design patent.

This application is a:

☐ continuation

☐ divisional


☒ continuation-in-part (CIP) of
prior application Serial No.
09/404,897, filed September 24, 1999.

2. Application Papers Enclosed

- Title Page
- 52 Pages of Specification (excluding Claims, Abstract & Drawings)
- 7 Page(s) of Claims
- 1 Page(s) of Abstract
- 14 Sheet(s) of Drawings (Figs. 1, 2, 3A, 3B, 4A, 4B, 4C, 5A, 5B, 6A, 6B, 7, 8
and 9)
- ☐ Formal
- ☒ Informal

CERTIFICATION UNDER 37 CFR 1.10

I hereby certify that this Patent Application Transmittal and the documents referred to as enclosed therewith are being deposited with the United States Postal Service on August 22, 2000, in an envelope addressed to the Assistant Commissioner for Patents, Washington, D.C. 20231 utilizing the "Express Mail Post Office to Addressee" service of the United States Postal Service under Mailing Label No. EL026003361US.



Robert W. Fieseler



09/643550 08/22/00

3. **Declaration or Oath**

☐ Enclosed

Executed by (check all applicable boxes)

☐ Inventor(s)

☐ Legal representative of inventor(s)

(37 CFR 1.42 or 1.43)

☐ Joint inventor or person showing a proprietary interest on behalf of inventor who refused to sign or cannot be reached

☐ The petition required by 37 CFR 1.47 and the statement required by 37 CFR 1.47 are enclosed. See Item 5D below for fee.

☒ Not enclosed - the undersigned attorney or agent is authorized to file this application on behalf of the applicant(s). An executed declaration will follow.

4. **Additional Papers Enclosed**

☐ Preliminary Amendment

☐ Information Disclosure Statement, including copies of cited references

☐ Declaration of Biological Deposit

☐ Computer readable copy of sequence listing containing nucleotide and/or amino acid sequence

☐ Verified statement(s) claiming small entity status under 37 CFR 1.9 and 1.27

☐ Associate Power of Attorney

☐ Verified translation of a non-English patent application

☐ An assignment of the invention

☐ Certified copy(ies) of application(s):

COUNTRY	APPLICATION NO.	FILED

from which priority under 35 USC 119 is claimed

☐ is(are) attached.

☐ will follow.

☐ Other

5. Filing Fee Calculation (37 CFR 1.16)

A. ☒ Utility Application

CLAIMS AS FILED - INCLUDING PRELIMINARY AMENDMENT (IF ANY)						
			SMALL ENTITY		OTHER THAN A SMALL ENTITY	
	NO. FILED	NO. EXTRA	RATE	FEE	RATE	FEE
BASIC FEE				\$345.00		\$ 690.00
TOTAL	42 - 20	= 22	X 9 =		X 18 =	\$ 396.00
INDEP.	2 - 3	= 0	X 39 =		X 78 =	\$ 0.00
<input checked="" type="checkbox"/> First Presentation of Multiple Dependent Claim			+ 130 =		+ 260 =	\$ 260.00
Filing Fee:				\$	OR	\$1346.00

B. ☐ Design Application (\$155.00/\$310.00) Filing Fee: \$ _____

C. ☐ Plant Application (\$240.00/\$480.00) Filing Fee: \$ _____

D. Other Fees

☐ Recording Assignment [Fee -- \$40.00 per assignment] \$ _____

☐ Petition fee for filing by other than all the inventors
or person on behalf of the inventor where inventor refused
to sign or cannot be reached [Fee -- \$130.00] \$ _____

☐ Other \$ _____

Total Fees Enclosed \$ 1346.00

6. Method of Payment of Fees

☒ Enclosed check in the amount of: \$ 1346.00

☐ Charge Deposit Account No. 13-0017 in the amount of: \$ _____
A copy of this Transmittal is enclosed.

☐ Not enclosed

	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307	2308	2309	2310	2311	2312	2313	2314	2315	2316	2317	2318	2319	2320	2321	2322	2323	2324	2325	2326	2327	2328	2329	2330	2331	2332	2333	2334	2335	2336	2337	2338	2339	2340	2341	2342	2343	2344	2345	2346	2347	2348	2349	2350	2351	2352	2353	2354	2355	2356	2357	2358	2359	2360	2361	2362	2363	2364	2365	2366	2367	2368	2369	2370	2371	2372	2373	2374	2375	2376	2377	2378	2379	2380	2381	2382	2383	2384	2385	2386	2387	2388	2389	2390	2391	2392	2393	2394	2395	2396	2397	2398	2399	2400	2401	2402	2403	2404	2405	2406	2407	2408	2409	2410	2411	2412	2413	2414	2415	2416	2417	2418	2419	2420	2421	2422	2423	2424	2425	2426	2427	2428	2429	2430	2431	2432	2433	2434	2435	2436	2437	2438	2439	2440	2441	2442	2
--	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	---

Please refund any overpayment to Deposit Account No. 13-0017.

McAndrews, Held & Malloy, Ltd.
500 West Madison Street, 34th Floor
Chicago, Illinois 60661

Respectfully submitted,

Robertson

Date: August 22, 2000

**FUEL CELL ANODE STRUCTURE FOR VOLTAGE REVERSAL
TOLERANCE**

Cross-Reference to Related Application

This is a continuation-in-part of application
Serial No. 09/404,897, filed on September 24,
1999, entitled "Solid Polymer Fuel Cell with
5 Improved Voltage Reversal Tolerance". This
application is related to and claims priority
benefits from U.S. Provisional Patent Application
Serial No. 60/150,253 filed August 23, 1999,
entitled "Fuel Cell Anode Structure for
10 Voltage Reversal Tolerance". The '897 application
and the '253 provisional application are each
incorporated herein by reference in their
entirety.

15 **Field of the Invention**

The present invention relates to an anode for
use in fuel cells, particularly solid polymer
electrolyte fuel cells, having improved tolerance
to voltage reversal, and to fuel cells comprising
20 said anode.

Background of the Invention

Fuel cell systems are currently being
developed for use as power supplies in numerous
25 applications, such as automobiles and stationary
power plants. Such systems offer promise of
delivering power economically and with
environmental and other benefits. To be

002280 "094960

5

10

20

25

30

react with the oxidant at the cathode electrocatalyst. The electrocatalysts are preferably located at the interfaces between each electrode and the adjacent electrolyte.

5 Solid polymer electrolyte fuel cells employ a
membrane electrode assembly ("MEA"), which
comprises the solid polymer electrolyte or ion-
exchange membrane disposed between the two
electrodes. Separator plates, or flow field
10 plates for directing the reactants across one
surface of each electrode substrate, are disposed
on each side of the MEA.

Each electrode contains an electrocatalyst layer, comprising an appropriate catalyst for facilitating the desired electrochemical reaction of the fuel and oxidant, located adjacent the solid polymer electrolyte. The electrocatalyst may be a metal black, an alloy or a supported metal catalyst, for example, platinum on carbon. The catalyst layer typically contains ionomer that may be similar to that used for the solid polymer electrolyte (for example, Nafion®). The catalyst layer may also contain a binder, such as polytetrafluoroethylene.

25 The electrodes may also contain a substrate
(typically a porous electrically conductive sheet
material) that may be employed for purposes of
reactant distribution and/or mechanical support.
Optionally, the electrodes may also contain a
30 sublayer (typically containing an electrically
conductive particulate material, for example

carbon black) between the catalyst layer and the substrate. A sublayer may be used to modify certain properties of the electrode (for example, interface resistance between the catalyst layer
5 and the substrate).

Electrodes for a MEA can be prepared by first applying a sublayer, if desired, to a suitable substrate, and then applying the catalyst layer onto the sublayer. These layers can be applied in
10 the form of slurries or inks that contain particulates and dissolved solids mixed in a suitable liquid carrier. The liquid carrier is then evaporated off to leave a layer of particulates and dispersed solids. Cathode and
15 anode electrodes may then be bonded to opposite sides of the membrane electrolyte via application of heat and/or pressure, or by other methods. Alternatively, catalyst layers may first be applied to the membrane electrolyte with optional
20 sublayers and substrates incorporated thereafter, either on the catalyzed membrane or an electrode substrate.

In operation, the output voltage of an individual fuel cell under load is generally below
25 one volt. Therefore, in order to provide greater output voltage, multiple cells are usually stacked together and are connected in series to create a higher voltage fuel cell stack. (End plate assemblies are placed at each end of the stack to
30 hold the stack together and to compress the stack components together. Compressive force effects

002220"0554960

sealing and provides adequate electrical contact between various stack components.) Fuel cell stacks can then be further connected in series and/or parallel combinations to form larger arrays
5 for delivering higher voltages and/or currents.

Electrochemical fuel cells are occasionally subjected to a voltage reversal condition, which is a situation in which the cell is forced to the opposite polarity. Opposite polarity may be
10 deliberately induced, as in the case of certain electrochemical devices known as regenerative fuel cells. (Regenerative fuel cells are designed and constructed to operate both as fuel cells and as electrolyzers in order to produce a supply of
15 reactants for fuel cell operation. Such devices have the capability of directing a water fluid stream to an electrode where, upon passage of an electric current, oxygen is formed. Hydrogen is formed at the other electrode.) Power-producing
20 electrochemical fuel cells connected in series are potentially subject to unwanted voltage reversals, however, such as when one of the cells is forced to the opposite polarity by the other cells in the series. In fuel cell stacks, this can occur when
25 a cell is unable to produce, from the electrochemical reactions occurring within it, the current being produced by the rest of the cells in the stack and that is being directed through the affected cell by virtue of its being in series
30 with the rest of the cells. Groups of cells within a stack can also undergo voltage reversal

002230"0554960

The adverse effects of voltage reversal can be prevented, for instance, by employing diodes capable of carrying the stack current across each individual fuel cell or by monitoring the voltage of each individual fuel cell and shutting down an affected stack if a low cell voltage is detected. Since stacks typically employ numerous fuel cells, however, such approaches can be quite complex and expensive to implement.

Alternatively, other conditions associated with voltage reversal may be monitored instead, and appropriate corrective action can be taken if reversal conditions or the onset of reversal conditions are detected. For instance, a specially constructed sensor cell may be employed that is more sensitive than other fuel cells in the stack to certain conditions leading to voltage reversal (for example, fuel starvation of the stack). Thus, instead of monitoring every cell in a stack, only the sensor cell need be monitored and used to prevent widespread cell voltage

reversal under such conditions. Other conditions leading to voltage reversal may exist that a sensor cell cannot detect, however (such as, for example, a defective individual cell in the stack). Another approach is to employ exhaust gas monitors that detect voltage reversal by detecting the presence of or abnormal amounts of species in an exhaust gas of a fuel cell stack that originate from reactions that occur during reversal. While exhaust gas monitors can detect a reversal condition occurring within any cell in a stack and may suggest the cause of reversal, such monitors do not specifically identify problem cells and they do not generally provide a warning of an impending voltage reversal.

Instead of or in combination with the preceding, a passive approach may be preferred such that, in the event that reversal does occur, the fuel cells are either more tolerant to the reversal or are controlled in such a way that degradation of critical hardware is reduced. A passive approach may be particularly preferred if the conditions leading to reversal are temporary. If the cells can be made more tolerant to voltage reversal, it may not be necessary to detect for reversal and/or shut down the fuel cell system during a temporary reversal period.

002280-054560

During voltage reve

A typical solid polymer electrolyte fuel cell comprises a cathode, an anode, a solid polymer electrolyte, an oxidant fluid stream directed to

A typical solid polymer electrolyte fuel cell comprises a cathode, an anode, a solid polymer electrolyte, an oxidant fluid stream directed to

the cathode and a fuel fluid stream directed to the anode.

In a reversal tolerant fuel cell, the anode comprises a first catalyst composition for evolving protons from the fuel and a second catalyst composition for evolving oxygen from water. The first catalyst composition is typically selected from the group consisting of precious metals, transition metals, oxides thereof, alloys thereof, and mixtures thereof. A preferred first catalyst composition for evolving protons from the fuel comprises platinum metal. For fuel cells operating on fuel streams containing carbon monoxide and carbon dioxide, an alloy of Pt/Ru is particularly preferred, which may for example be unsupported or supported at various loadings, such as 20%/10% by weight Pt/Ru or 40%/20% by weight Pt/Ru. Other compositions may be preferred depending on fuel type (for example, Pt metal for gaseous hydrogen).

The second catalyst composition is incorporated for purposes of electrolyzing water at the anode during voltage reversal situations. Preferred compositions thus include precious metal oxides, particularly those in the group consisting of ruthenium oxide and iridium oxide. Such oxides are characterized by the chemical formulae RuO_x and IrO_x , where x is greater than 1 and particularly about 2. Preferred compositions may also comprise mixtures and solid solutions of precious metal oxides, or mixtures and solid

002220-055450

solutions of precious metal oxides and valve metal oxides, such as TiO_y (where y is less than or about equal to 2), for example.

002280"034960

5 Either or both of the first and second catalyst compositions may be unsupported or, instead, supported on a suitable electrically conductive supporting material, such as carbon, titanium oxides (for example, Ti_4O_7), other valve metal oxides, or any combination thereof. Carbon
10 is a preferred support for either catalyst composition (for example, acetylene or furnace blacks). Two different support materials (that is, first and second supports) may be employed for the first and second catalyst compositions or the
15 two compositions may be deposited on the same supporting powder. In the case of the latter, the second composition may be deposited on the support after the first composition is deposited. For instance, the voltage reversal tolerance of an
20 anode comprising carbon supported Pt/Ru alloy (for example, nominally 20/10 per cent by weight of Pt/Ru) may be improved by depositing RuO_2 thereon (for example, nominally 20% by weight Ru).

25 The first and second catalyst compositions may be incorporated in one or more common layers in the anode, for example by depositing both on the same support and applying to a suitable substrate or by mixing the two catalyst compositions and applying the mixture to a
30 suitable substrate in one or more layers. Alternatively, the first and second catalyst

compositions may be incorporated in separate layers in the anode, for example by applying the two catalyst compositions to a suitable anode substrate in two separate layers thereby forming a bilayer anode.

Brief Description of the Drawings

FIG. 1 is a schematic diagram of a solid polymer fuel cell.

FIG. 2 is a representative composite plot of voltage as a function of time, as well as the currents consumed generating carbon dioxide and oxygen as a function of time, respectively, for a conventional solid polymer fuel cell undergoing fuel starvation.

FIGs. 3A and 3B show the x-ray diffraction patterns of catalyst samples C1 and C3 in the Examples, respectively.

FIGs. 4A, 4B and 4C are Tafel plots of ex-situ oxygen evolution for catalyst compositions C1, C6-C10, and C12-C14 in the Examples.

FIGs. 5A and 5B are composite plots of voltage as a function of time, as well as the currents consumed in the production of CO₂ as a function of time, respectively, for cells FC1-FC6 in the Examples during the first voltage reversal period.

FIGs. 6A and 6B are composite plots of voltage as a function of time, as well as the currents consumed in the production of CO₂ as a function of time, respectively, for cells FC2/6,

FC6/2, and FC2+6 in the Examples during the first voltage reversal period.

FIG. 7 is a plot of voltage as a function of time for selected cells in the Examples during the
5 second voltage reversal test.

FIG. 8 is a plot of voltage as a function of time for cells FCR1, FCR1+6, FCR1+10, and FCR1+11 in the Examples during the step 3 of the voltage reversal test.


10 FIG. 9 is a plot of voltage as a function of time for cells FCR1+6, FCR1+13 and FCR1+14 in the Examples during steps 1 and 2 of the voltage reversal testing.

15 **Detailed Description of Preferred Embodiment(s)**


Voltage reversal occurs when a fuel cell in a series stack cannot generate sufficient current to keep up with the rest of the cells in the series stack. Several conditions can lead to voltage
20 reversal in a solid polymer fuel cell, for example, including insufficient oxidant, insufficient fuel, insufficient water, low or high cell temperatures, and certain problems with cell components or construction. Reversal generally
25 occurs when one or more cells experience a more extreme level of one of these conditions compared to other cells in the stack. While each of these conditions can result in negative fuel cell voltages, the mechanisms and consequences of such
30 a reversal may differ depending on which condition caused the reversal.

002280"0354960

During normal operation of a solid polymer fuel cell on hydrogen fuel, for example, the following electrochemical reactions take place:



However, with insufficient oxidant (oxygen)
10 present, the protons produced at the anode cross the electrolyte and combine with electrons directly at the cathode to produce hydrogen gas. The anode reaction and thus the anode potential remain unchanged. However, the absolute potential
15 of the cathode drops and the reaction is



20 In this case, the fuel cell is operating like a hydrogen pump. Since the oxidation of hydrogen gas and the reduction of protons are both very facile (that is, small overpotential), the voltage across the fuel cell during this type of reversal
25 is quite small. Hydrogen production actually begins at small positive cell voltages (for example, 0.03 V) because of the large hydrogen concentration difference present in the cell. The cell voltage observed during this type of reversal
30 depends on several factors (including the current and cell construction) but, at current densities

002230" 0554960


of about 0.5 A/cm^2 , the fuel cell voltage may typically be less than or about -0.1 V .

An insufficient oxidant condition can arise when there is water flooding in the cathode, oxidant supply problems, and the like. Such conditions then lead to low magnitude voltage reversals with hydrogen being produced at the cathode. Significant heat is also generated in the affected cell(s). These effects raise potential reliability concerns, however the low potential experienced at the cathode does not typically pose a significant corrosion problem for the cathode components. Nonetheless, some degradation of the membrane might occur from the lack of water production and from the heat generated during reversal. The continued production of hydrogen may also result in some damage to the cathode catalyst.


A different scenario takes place when there is insufficient fuel present. In this case, the cathode reaction and thus the cathode potential remain unchanged. However, the anode potential rises to the potential for water electrolysis. Then, as long as water is available, electrolysis takes place at the anode. However, the potential of the anode is then generally high enough to significantly start oxidizing typical components used in the anode, for example, the carbons employed as supports for the catalyst or the electrode substrates. Thus, some anode component oxidation typically occurs along with

electrolysis. (Thermodynamically, oxidation of the carbon components actually starts to occur before electrolysis. However, it has been found that electrolysis appears kinetically preferred and thus proceeds at a greater rate.) The reactions in the presence of oxidizable carbon-based components are typically:

at the anode, in the absence of fuel:



and



More current can be sustained by the electrolysis reaction if more water is available at the anode. However, if not consumed in the electrolysis of water, current is instead used in the corrosion of the anode components. If the supply of water at the anode runs out, the anode potential rises further and the corrosion rate of the anode components increases. Thus, there is preferably an ample supply of water at the anode in order to prevent degradation of the anode components during reversal.

25 The voltage of a fuel cell experiencing fuel starvation is generally much lower than that of a fuel cell receiving insufficient oxidant. During reversal from fuel starvation, the cell voltage ranges around -1 V when most of the current is carried by water electrolysis. However, when electrolysis cannot sustain the current (for

example, if the supply of water runs out or is inaccessible), the cell voltage can drop substantially (much less than -1 V) and is theoretically limited only by the voltage of the remaining cells in the series stack. Current is then carried by corrosion reactions of the anode components or through electrical shorts, including dielectric breakdown of the membrane electrolyte, which may develop as a result. Additionally, the cell may dry out, leading to very high ionic resistance and further heating. The impedance of the reversed cell may increase such that the cell is unable to carry the current provided by the other cells in the stack, thereby further reducing the output power provided by the stack.

Fuel starvation can arise when there is severe water flooding at the anode, fuel supply problems, and the like. Such conditions can lead to high magnitude voltage reversals (that is, much less than -1 V) with oxygen and carbon dioxide being produced at the anode. Significant heat is again generated in the reversed cell. These effects raise more serious reliability concerns than in an oxidant starvation condition. Very high potentials may be experienced at the anode, thereby posing a serious anode corrosion, and hence reliability, concern.

Voltage reversals may also originate from low fuel cell temperatures, for example at start-up. Cell performance decreases at low temperatures for kinetic, cell resistance, and mass transport

00220-03430

002230"0354960
limitation reasons. Voltage reversal may then
occur in a cell whose temperature is lower than
the others due to a temperature gradient during
start-up. Reversal may also occur in a cell
5 because of impedance differences that are
amplified at lower temperatures. When voltage
reversal is due solely to such low temperature
effects, however, the normal reactants are
generally still present at both the anode and
10 cathode (unless, for example, ice has formed so as
to block the flowfields). In this case, voltage
reversal is caused by an increase in overpotential
only. The current forced through the reversed
cell still drives the normal reactions to occur
15 and thus the aforementioned corrosion issues
arising from a reactant starvation condition are
less of a concern. (With higher anode potentials,
however, anode components may also be oxidized.)
This type of reversal is primarily a performance
20 issue that is resolved when the stack reaches a
normal operating temperature.

Problems with certain cell components and/or
construction can also lead to voltage reversals.
For instance, a lack of catalyst on an electrode
25 due to manufacturing error would render a cell
incapable of providing normal output current.
Similarly degradation of catalyst or another
component for other reasons could render a cell
incapable of providing normal output current.

30 In the present approach, fuel cells are
rendered more tolerant to voltage reversal by

incorporating an additional catalyst composition at the anode to further promote water electrolysis during cell voltage reversal. It is thus advantageous in situations where electrolyzing
5 more water is beneficial (for example, during fuel starvation).

FIG. 1 shows a schematic diagram of a solid polymer fuel cell. Solid polymer fuel cell 1 comprises anode 2, cathode 3, and solid polymer
10 electrolyte 4. Both anode and cathode typically employ catalysts supported on carbon powders that are mounted in turn upon porous carbonaceous substrates. A fuel stream is supplied at fuel inlet 5 and an oxidant stream is supplied at
15 oxidant inlet 6. The reactant streams are exhausted at fuel and oxidant outlets 7 and 8 respectively. In the absence of fuel, water electrolysis and oxidation of the carbon components in the anode may occur.

20 FIG. 2 is a representative plot of voltage as a function of time for a conventional solid polymer fuel cell undergoing fuel starvation. (The fuel cell anode and cathode comprised carbon-supported Pt/Ru and Pt electrocatalysts,
25 respectively, on carbon fiber paper substrates.) In this case, a stack reversal situation was simulated by using a constant current (10 A) power supply to drive current through the cell, and a fuel starvation condition was created by flowing
30 humidified nitrogen (100% relative humidity (RH)) across the anode instead of the fuel stream. The

002280"06450

exhaust gases at the fuel outlet of this conventional fuel cell were analyzed by gas chromatography during the simulated fuel starvation. The rates at which oxygen and carbon dioxide appeared in the anode exhaust were determined and used to calculate the current consumed in producing each gas also shown in FIG. 2.

As shown in FIG. 2, the cell quickly went into reversal and dropped to a voltage of about -0.6 V. The cell voltage was then roughly stable for about 8 minutes, with only a slight increase in overvoltage with time. During this period, most of the current was consumed in the generation of oxygen via electrolysis ($\text{H}_2\text{O} \rightarrow \frac{1}{2}\text{O}_2 + 2\text{H}^+ + 2\text{e}^-$). A small amount of current was consumed in the generation of carbon dioxide ($\frac{1}{2}\text{C} + \text{H}_2\text{O} \rightarrow \frac{1}{2}\text{CO}_2 + 2\text{H}^+ + 2\text{e}^-$). The electrolysis reaction thus sustained most of the reversal current during this period at a rough voltage plateau from about -0.6 to -0.9V. At that point, it appeared that electrolysis could no longer sustain the current and the cell voltage dropped abruptly to about -1.4 V. Another voltage plateau developed briefly, lasting about 2 minutes. During this period, the amount of current consumed in the generation of carbon dioxide increased rapidly, while the amount of current consumed in the generation of oxygen decreased rapidly. On this second voltage plateau therefore, significantly more carbon was oxidized in the anode than on the

first voltage plateau. After about 11 minutes, the cell voltage dropped off quickly again. Typically thereafter, the cell voltage continued to fall rapidly to very negative voltages (not shown) until an internal electrical short developed in the fuel cell (representing a complete cell failure). Herein, the inflection point at the end of the first voltage plateau is considered as indicating the end of the electrolysis period. The inflection point at the end of the second plateau is considered as indicating the point beyond which complete cell failure can be expected.

Without being bound by theory, the electrolysis reaction observed at cell voltages between about -0.6 V and about -0.9 V is presumed to occur because there is water present at the anode catalyst and the catalyst is electrochemically active. The end of the electrolysis plateau in FIG. 2 may indicate an exhaustion of water in the vicinity of the catalyst or loss of catalyst activity (for example, by loss of electrical contact to some extent). The reactions occurring at cell voltages of about -1.4 V would presumably require water to be present in the vicinity of anode carbon material without being in the vicinity of, or at least accessible to, active catalyst (otherwise electrolysis would be expected to occur instead). The internal shorts that develop after prolonged reversal to very negative voltages appear to stem

002280"054950

from severe local heating which occurs inside the membrane electrode assembly, which may melt the polymer electrolyte, and create holes that allow the anode and cathode electrodes to touch.

5 In practice, a minor adverse effect on subsequent fuel cell performance may be expected after the cell has been driven into the electrolysis regime during voltage reversal (that is, driven onto the first voltage plateau). For
10 instance, a 50 mV drop may be observed in subsequent output voltage at a given current for a fuel cell using carbon-supported anode catalyst. (It has been found however that fuel cells using unsupported anode catalysts, for example platinum
15 blacks, are less degraded when subjected to cell reversal.) More of an adverse effect on subsequent fuel cell performance (for example, 150 mV drop) will likely occur after the cell has been driven into reversal onto the second voltage
20 plateau. Beyond that, complete cell failure can be expected as a result of internal shorting. Thus, if a cell is going to be subjected to a voltage reversal situation, it seems preferable to promote electrolysis and also to extend the period
25 of electrolysis, thereby limiting the negative voltage experienced by the cell and thereby reducing degradation and making it less likely that the cell will be exposed to more serious reversal conditions.

30 Incorporating an additional or second catalyst composition at the anode for purposes of

002230"0554360

The second catalyst composition may comprise mixtures and/or solid solutions of precious metal oxides, or mixtures and/or solid solutions of precious metal oxides and valve metal oxides, such as TiO_y (where y is less than or about equal to 2), for example. (See K. Kinoshita, Electrochemical Oxygen Technology, pp. 342-46, J. Wiley & Sons, New York, 1992). A valve metal is defined as "one that is capable of forming a

The second catalyst composition may comprise mixtures and/or solid solutions of precious metal oxides, or mixtures and/or solid solutions of precious metal oxides and valve metal oxides, such as TiO_y (where y is less than or about equal to 2), for example. (See K. Kinoshita, Electrochemical Oxygen Technology, pp. 342-46, J. Wiley & Sons, New York, 1992). A valve metal is defined as "one that is capable of forming a

protective oxide coating when employed as the anode of an electrochemical cell" (Kirk-Othmer Encyclopaedia of Chemical Technology, Vol. 10, p. 248, 3rd Ed., J. Wiley & Sons, New York, 1980) but
5 from an electrochemical point of view the following are the most appropriate: hafnium, niobium, tantalum, titanium, tungsten and zirconium.

Ruthenium oxide (rutile form, RuO_x where $1 < x \leq 2$) is the more active catalyst for oxygen
10 evolution and thus seems to be a preferred second catalyst composition. However, if a voltage reversal is prolonged or if there is sufficient cumulative time in reversal, the ruthenium oxide
15 may be further oxidized to RuO_3 or RuO_4 and may dissolve in the membrane electrolyte. Iridium oxide is not as active for oxygen evolution but is more stable than ruthenium oxide. Thus, IrO_x may be preferred if prolonged reversals are a concern.
20 A mixture or solid solution of ruthenium and iridium oxides may afford a preferred combination of low oxygen overpotential and stability. A mixture or solid solution of ruthenium oxide and a valve metal oxide, such as titanium dioxide, for
25 example, may afford another preferred combination for low oxygen overpotential and stability.

The second catalyst composition may either be unsupported or supported in dispersed form on a suitable electrically conducting particulate
30 support. If desired, the second catalyst composition may even be supported on the same

002280"0554950

support as the first catalyst composition. (For instance, the first catalyst composition may be deposited on a suitable support initially and then the second catalyst composition may be deposited thereon afterwards.) High surface area carbons such as acetylene or furnace blacks are commonly used as supports for such catalysts. Preferably, the support used is itself tolerant to voltage reversal. Thus, it is desirable to consider using carbon supports that are more corrosion resistant (for example, more graphitic carbons).

Instead of carbon, an electrically conductive titanium oxide may be considered as a suitable high surface area support for the second catalyst composition. For instance, Ti_4O_7 may serve as a suitable supported second catalyst composition. In this regard, other valve metal oxides might be considered as well if they have acceptable electronic conductivity when acting as supports for the second catalyst composition.

The amount of the second catalyst composition that is desirably incorporated will depend on such factors as the fuel cell stack construction and operating conditions (for example, current that may be expected in reversal), cost, and so on. It is expected that some empirical trials will determine an optimum amount for a given application.

The second catalyst composition may be incorporated in the anode in various ways. Preferably, it is located where water is readily

002230-034350

available and such that it can favorably compete with the other oxidation reactions that degrade the anode structure. For instance, the first and second catalyst compositions may be mixed together
5 and the mixture applied in a common layer or layers on a suitable anode substrate.

Alternatively, as mentioned above, the second catalyst composition may be supported on the same support as the first composition, and thus both
10 compositions are already "mixed" for application in one or more layers on an anode substrate. Further however, the two compositions may instead be applied in separate layers on an anode substrate, thereby making a bilayer or multilayer
15 anode structure where the first and second catalyst compositions are in discrete layers. This may be advantageous in certain embodiments.

Along with promoting electrolysis during reversal via the incorporation of an additional
20 catalyst composition, other modifications might desirably be adopted to improve tolerance to voltage reversal. For instance, component and/or structural modifications to the anode may be useful in providing and maintaining more water in
25 the vicinity of the anode catalyst during voltage reversal. The use of an ionomer with a higher water content in the catalyst layer would be an example of a component modification that would result in more water in the vicinity of the anode
30 catalyst. Tolerance to voltage reversal might also be improved by employing more corrosion

002280"0554950

resistant anode components (for example, graphite or titanium oxide supports) or by protecting the components against corrosion using other methods (for example, by covering the exposed areas of the supports with more catalyst thereby protecting their surface).

The following examples illustrate certain embodiments and aspects of the invention. However, these examples should not be construed as limiting in any way.

Examples

A series of catalyst samples were prepared in order to evaluate ex-situ oxygen evolution performance to compare their potential ability to improve anode tolerance during voltage reversal in a fuel cell. The catalyst compositions were prepared on carbon supports as indicated below.

20

The catalyst samples prepared were:

C1: Pt/Ru alloy supported on Shawinigan acetylene black (from Chevron Chemical Company, Texas, USA), nominally 20% Pt/10% Ru by weight (the remainder being carbon);

25

C2: Pt/Ru alloy supported on Vulcan XC72R grade furnace black (from Cabot Carbon Ltd., South Wirral, UK), nominally 20% Pt/10% Ru by weight;

- C3: Pt/Ru alloy and RuO₂ supported on Shawinigan acetylene black, nominally 16% Pt/8% Ru (as alloy)/20% Ru (as RuO₂) by weight;
- 5 C4: Pt/Ru alloy and RuO₂ supported on Vulcan XC72R grade furnace black, nominally 16% Pt/8% Ru (as alloy)/20% Ru (as RuO₂) by weight;
- 10 C5: Pt/Ru alloy and RuO₂ supported on graphitized Vulcan XC72R grade furnace black (graphitized at temperatures above 2500°C), nominally 16% Pt/8% Ru (as alloy)/20% Ru (as RuO₂) by weight;
- 15 C6: RuO₂ supported on Shawinigan acetylene black, nominally 20% Ru (as oxide) by weight (remainder carbon and oxygen);
- C7: IrO₂ supported on Shawinigan acetylene black, nominally 20% Ir (as oxide) by weight (remainder carbon and oxygen);
- 20 C8: RuO₂/TiO₂ supported on Shawinigan acetylene black, nominally 20% Ru (as oxide) by weight and a 50:50 atomic Ru/Ti ratio;
- C9: RuO₂/TiO₂ supported on Shawinigan acetylene black, nominally 20% Ru (as oxide) by weight and a 70:30 atomic Ru/Ti ratio;
- 25 C10: RuO₂/TiO₂ supported on Shawinigan acetylene black, nominally 20% Ru (as oxide) by weight and a 90:10 atomic Ru/Ti ratio;
- 30 C11: RuO₂/IrO₂ supported on Shawinigan acetylene black, nominally 20% Ru (as oxide) by weight and a 90:10 atomic Ru/Ir ratio;

002220"0554960

C12: IrO₂/TiO₂ supported on Shawinigan acetylene black, nominally 20% Ir (as oxide) by weight and a 90:10 atomic Ir/Ti ratio;

5 C13: RuO₂ supported on Shawinigan acetylene black, nominally 20% Ru (as oxide) by weight (remainder carbon and oxygen);

C14: RuO₂ supported on Shawinigan acetylene black, nominally 20% Ru (as oxide) by weight (remainder carbon and oxygen).

10

In terms of the corrosion resistance of the carbon supports, the order of corrosion resistance is Vulcan XC72R (graphitized) > Shawinigan > Vulcan XC72R. This order of corrosion resistance is
15 related to the graphitic nature of the carbon supports. The more graphitic the support, the more corrosion resistant the support. The graphitic nature of a carbon is exemplified by the carbon inter-layer separation d_{002} measured from
20 the x-ray diffractograms. Synthetic graphite (essentially pure graphite) has a spacing of 3.36 Å compared with 3.45 Å for Vulcan XC72R (graphitized), 3.50 Å for Shawinigan, and 3.64 Å for Vulcan XC72R, with the higher inter-layer
25 separations reflecting the decreasing graphitic nature of the carbon support and the decreasing order of corrosion resistance. Another indication of the corrosion resistance of the carbon supports is provided by the BET surface area measured using
30 nitrogen. Vulcan XC72R has a surface area of about 200 m²/g. This contrasts with a surface

002220"0554960

area of about 80 m²/g for Vulcan (graphitized). The much lower surface area as a result of the graphitization process reflects a loss in the more corrodible microporosity in Vulcan XC72R. The
5 microporosity is commonly defined as the surface area contained in the pores of a diameter less than 20 Å. Shawinigan has a surface area of about 80 m²/g, and BET analysis indicates a low level of corrodible microporosity available in this
10 support.

For samples C1-C5, a conventional nominal 1:1 atomic ratio Pt/Ru alloy was deposited onto the indicated carbon support first. This was accomplished by making a slurry of the carbon
15 black in demineralized water. Sodium bicarbonate was then added and the slurry was boiled for thirty minutes. A mixed solution comprising H₂PtCl₆ and RuCl₃ in an appropriate ratio was added while still boiling. The slurry was then cooled,
20 formaldehyde solution was added, and the slurry was boiled again. The slurry was then filtered and the filter cake was washed with demineralized water on the filter bed until the filtrate was free of soluble chloride ions (as detected by a
25 standard silver nitrate test). The filter cake was then oven dried at 105°C in air, providing nominally 20%/10% Pt/Ru alloy carbon supported samples.

For samples C3-C5, a RuO₂ catalyst
30 composition was formed on a previously prepared carbon supported Pt/Ru catalyst composition. This

002280-0564960

was accomplished by making a slurry of the carbon supported Pt/Ru sample in boiling demineralized water. Potassium bicarbonate was added next and then RuCl_3 solution in an appropriate ratio while
5 still boiling. The slurry was then cooled, filtered and filter cake washed with demineralized water as above until the filtrate was free of soluble chloride ions (as detected by a standard silver nitrate test). The filter cake was then
10 oven dried at 105°C in air until there was no further mass change. Finally, each sample was placed in a controlled atmosphere oven and heated for two hours at 350°C under nitrogen.

Sample C6 was prepared in a like manner to
15 C3-C5 except that the RuO_2 catalyst composition was deposited directly onto uncatalyzed Shawinigan acetylene black.

For sample C7, an IrO_2 catalyst composition was formed on a carbon support. This was
20 accomplished by making a slurry of the carbon black in boiling demineralized water. Sodium bicarbonate was added next and then IrCl_3 solution in an appropriate ratio while still boiling. The slurry was then cooled, filtered and the filter
25 cake washed with demineralized water as above until the filtrate was free of soluble chloride ions (as detected by a standard silver nitrate test). The filter cake was then oven dried at
30 105°C in air until there was no further mass change. Finally, the sample was placed in a

002220"034960

controlled atmosphere oven and heated for four hours at 350°C under nitrogen.

For sample C8, a catalyst composition comprising a solid solution of $\text{RuO}_2/\text{TiO}_2$ was formed on a carbon support. This was accomplished by making a slurry of the carbon black in boiling demineralized water. Sodium bicarbonate was added next, followed by a mixed solution comprising RuCl_3 and TiCl_3 in an appropriate ratio while still boiling. The slurry was then cooled, filtered and the filter cake washed with demineralized water as above until the filtrate was free of soluble chloride ions (as detected by a standard silver nitrate test). The filter cake was then oven dried at 105°C in air until there was no further mass change. Finally, the sample was placed in a controlled atmosphere oven and heated for two hours at 350°C under nitrogen.

Samples C9 and C10 were prepared in a like manner to C8, except that the mixed solution added to the slurry contained the appropriate ratios of RuCl_3 and TiCl_3 , and the dried filter cakes were placed in a controlled atmosphere oven and heated for four hours at 350°C under nitrogen.

For sample C11, a catalyst composition comprising a solid solution of $\text{RuO}_2/\text{IrO}_2$ was formed on a carbon support. This was accomplished by making a slurry of the carbon black in boiling demineralized water. Sodium bicarbonate was added next, followed by a mixed solution comprising RuCl_3 and IrCl_3 in an appropriate ratio while

002220"055450

5

10

30

Sample C14 was prepared in a like manner to C6, except that the dried filter cake was placed

in an oven and heated in air at 180 °C for two hours.

Sample C1 was assayed and was determined to contain 19.8% Pt and 9.6% Ru by weight. An x-ray
5 diffraction pattern using Cu K α radiation for this sample is shown in FIG. 3A. The pattern shows four major diffraction peaks for a single phase Pt crystalline material, with a cubic
lattice structure, and the moderately graphitic
10 carbon support ($2\theta = 26^\circ$) only. The face centered cubic lattice parameter for the Pt based peaks indicate some incorporation of Ru into the Pt cubic lattice. The analysis suggested that not
all of the Ru was incorporated into the alloy and
15 some unalloyed amorphous hydrous ruthenium oxide remained. Based on the analysis of the {111} and {220} reflections, the average crystallite size of the Pt based particles was determined to be 2.65 nm.

20 Sample C2 was assayed and was determined to contain 19.8% Pt and 9.3% Ru by weight. An x-ray diffraction pattern was recorded for this sample and showed that the only crystalline phase present was face centered cubic Pt (data not shown). A
25 determination of the lattice parameter indicates some incorporation of Ru into the Pt lattice. The average crystallite size of the Pt was determined to be 1.9 nm.

Sample C3 was also assayed and was determined
30 to contain 14.7% Pt and 25.5% Ru by weight (nominally 15%Pt and 26% Ru, assuming that all the

002280 054560

Ru from the first deposition step was present as metallic Ru alloyed with Pt and that all the Ru added in the second deposition step was present as RuO₂). An x-ray diffraction pattern for this sample is shown in FIG. 3B. The pattern shows peaks similar to those in FIG. 3A indicating that the Pt based phase remained substantially unchanged. Additionally now, peaks corresponding to a crystalline tetragonal RuO₂ (rutile) phase were observed (major peaks at 2θ angles of 28, 35, and 54°). The diffraction peak due to the graphitic nature of the carbon support remains as a shoulder peak at 26° on the edge of the major RuO₂ diffraction. The average crystallite size of the RuO₂ was determined to be 4.8 nm. No hexagonal metallic ruthenium phase or other additional phases were observed. Thus, sample C3 appears to contain two distinct crystalline catalyst phases.

Sample C4 was assayed and determined to contain 15.1% Pt and 25.0% Ru by weight. An x-ray diffraction pattern was recorded for this sample and showed the presence of both poorly crystalline face centered cubic Pt and tetragonal (rutile) RuO₂. The average crystallite size of RuO₂ was determined to be 3.7 nm.

Sample C5 was assayed and was determined to contain 12.1% Pt and 15.7% Ru by weight. An x-ray diffraction pattern was recorded for this sample and showed the presence of both poorly crystalline face centered cubic Pt and tetragonal (rutile)

RuO₂. The average crystallite size of the RuO₂ could not be determined due to overlaps with cubic Pt peaks in the diffraction pattern.

Samples C6, C13 and C14 were assayed and were
5 determined to contain 17.9%, 18.9%, and 19.0% Ru
by weight, respectively. The samples were
analyzed by x-ray diffraction, which showed the
presence of crystalline tetragonal (rutile) RuO₂
in all three samples. The average crystallite
10 size of the RuO₂ was determined to be 3.5, 2.2 and
13.0 nm for C6, C13 and C14, respectively. No
hexagonal ruthenium metallic phase or additional
crystalline phases were observed.

Samples C7 and C12 were assayed and were
15 determined to contain 18.6% Ir, and 16.4% Ir and
0.5% Ti by weight, respectively. The samples were
analyzed by x-ray diffraction, which showed a
small amount of face centered cubic iridium metal,
in the case of C12. No other crystalline phases
20 were observed, indicating that the remainder of
the Ir and Ti oxides were present as amorphous
phases.

Samples C8, C9 and C10 were assayed and were
determined to contain 15.8% Ru and 7.8% Ti, 17.6%
25 Ru and 3.6% Ti, and 17.4% Ru and 1.0% Ti by
weight, respectively. The samples were analyzed
by x-ray diffraction, which showed the presence of
poorly crystalline tetragonal phase in each case.
For C8, a determination of the lattice parameter
30 from the x-ray diffraction pattern showed it to be
identical to RuO₂, indicating little if any

002229"035E4960

incorporation of TiO_2 into the RuO_2 lattice.
However, no indication of crystalline TiO_2 was
found in the sample. For C9, a determination of
the lattice parameter did indicate some
5 incorporation of TiO_2 into the RuO_2 lattice.
Again, no separate crystalline TiO_2 phase was
observed. For C10, a determination of the lattice
parameter showed it to be identical to RuO_2 ,
although at this low proportion of TiO_2 it is
10 unlikely that a shift in the lattice parameter
caused by the presence of TiO_2 in the RuO_2 lattice
could be observed.

Sample C11 was assayed and determined to
contain 16.2% Ru and 3.2% Ir by weight. X-ray
15 diffraction analysis indicated the sample
contained a poorly crystalline tetragonal (rutile)
phase. A determination of the lattice parameter
showed it to be indistinguishable from that of
 RuO_2 and IrO_2 . Given that the lattice parameters
20 of RuO_2 and IrO_2 are very similar, it was not
possible to conclude whether the Ru and Ir were
present as a single phase, or two separate phases.

Ex-situ oxygen evolution performance of the
preceding catalyst compositions was evaluated as
25 indicated below.

Tests were performed on a glassy carbon
rotating-disk electrode (RDE) with a rotation rate
of 1000 rpm in 0.5 M H_2SO_4 at a temperature of
80°C. Test samples were prepared by suspending
30 0.020 g of the catalyst composition powder in 2 ml
ethanoic acid. A micropipette was used to apply 2

002280-034360

Variable	Mean	SD	Min	Max	Skewness	Kurtosis	Normality test
Age	34.5	10.2	20	65	0.15	3.2	0.98
Gender	0.5	0.5	0	1	0.0	3.0	0.99
Marital status	0.6	0.5	0	1	0.0	3.0	0.99
Education	12.5	2.5	9	16	0.1	3.1	0.98
Income	1500	500	500	3000	0.2	3.3	0.97
Health status	0.7	0.4	0	1	0.0	3.0	0.99
Stress level	3.5	1.5	1	6	0.1	3.1	0.98
Life satisfaction	4.2	1.2	1	7	0.1	3.1	0.98
Resilience	5.5	1.5	1	7	0.1	3.1	0.98
Optimism	5.8	1.2	1	7	0.1	3.1	0.98
Emotional stability	5.2	1.3	1	7	0.1	3.1	0.98
Self-efficacy	5.0	1.4	1	7	0.1	3.1	0.98
Perceived social support	4.5	1.1	1	7	0.1	3.1	0.98
Life events	2.5	1.0	1	5	0.1	3.1	0.98
Life stressors	3.0	1.2	1	6	0.1	3.1	0.98
Life challenges	3.2	1.3	1	6	0.1	3.1	0.98
Life difficulties	3.1	1.4	1	6	0.1	3.1	0.98
Life setbacks	3.3	1.5	1	6	0.1	3.1	0.98
Life hardships	3.4	1.6	1	6	0.1	3.1	0.98
Life tribulations	3.5	1.7	1	6	0.1	3.1	0.98
Life adversities	3.6	1.8	1	6	0.1	3.1	0.98
Life trials	3.7	1.9	1	6	0.1	3.1	0.98
Life ordeals	3.8	2.0	1	6	0.1	3.1	0.98
Life vicissitudes	3.9	2.1	1	6	0.1	3.1	0.98
Life tribulations	4.0	2.2	1	6	0.1	3.1	0.98
Life hardships	4.1	2.3	1	6	0.1	3.1	0.98
Life setbacks	4.2	2.4	1	6	0.1	3.1	0.98
Life difficulties	4.3	2.5	1	6	0.1	3.1	0.98
Life challenges	4.4	2.6	1	6	0.1	3.1	0.98
Life stressors	4.5	2.7	1	6	0.1	3.1	0.98
Life events	4.6	2.8	1	6	0.1	3.1	0.98
Life tribulations	4.7	2.9	1	6	0.1	3.1	0.98
Life hardships	4.8	3.0	1	6	0.1	3.1	0.98
Life setbacks	4.9	3.1	1	6	0.1	3.1	0.98
Life difficulties	5.0	3.2	1	6	0.1	3.1	0.98
Life challenges	5.1	3.3	1	6	0.1	3.1	0.98
Life stressors	5.2	3.4	1	6	0.1	3.1	0.98
Life events	5.3	3.5	1	6	0.1	3.1	0.98
Life tribulations	5.4	3.6	1	6	0.1	3.1	0.98
Life hardships	5.5	3.7	1	6	0.1	3.1	0.98
Life setbacks	5.6	3.8	1	6	0.1	3.1	0.98
Life difficulties	5.7	3.9	1	6	0.1	3.1	0.98
Life challenges	5.8	4.0	1	6	0.1	3.1	0.98
Life stressors	5.9	4.1	1	6	0.1	3.1	0.98
Life events	6.0	4.2	1	6	0.1	3.1	0.98
Life tribulations	6.1	4.3	1	6	0.1	3.1	0.98
Life hardships	6.2	4.4	1	6	0.1	3.1	0.98
Life setbacks	6.3	4.5	1	6	0.1	3.1	0.98
Life difficulties	6.4	4.6	1	6	0.1	3.1	0.98
Life challenges	6.5	4.7	1	6	0.1	3.1	0.98
Life stressors	6.6	4.8	1	6	0.1	3.1	0.98
Life events	6.7	4.9	1	6	0.1	3.1	0.98
Life tribulations	6.8	5.0	1	6	0.1	3.1	0.98

Variable	Mean	SD	Min	Max	Skewness	Kurtosis	Normality test
Age	34.5	10.2	20	65	0.15	3.2	0.98
Gender	0.5	0.5	0	1	0.0	3.0	0.99
Marital status	0.6	0.5	0	1	0.0	3.0	0.99
Education	12.5	2.5	9	16	0.1	3.1	0.98
Income	1500	500	500	3000	0.2	3.3	0.97
Health status	0.7	0.4	0	1	0.0	3.0	0.99
Stress level	3.5	1.5	1	6	0.1	3.1	0.98
Life satisfaction	4.2	1.2	1	7	0.1	3.1	0.98
Work engagement	4.5	1.0	1	7	0.1	3.1	0.98
Organizational commitment	4.8	1.1	1	7	0.1	3.1	0.98
Turnover intention	1.5	1.0	0	4	0.1	3.1	0.98
Job satisfaction	4.0	1.0	1	7	0.1	3.1	0.98
Perceived stress	3.0	1.0	1	6	0.1	3.1	0.98
Work-life balance	4.0	1.0	1	7	0.1	3.1	0.98
Organizational citizenship behavior	4.5	1.0	1	7	0.1	3.1	0.98
Employee well-being	4.5	1.0	1	7	0.1	3.1	0.98
Job burnout	2.5	1.0	1	6	0.1	3.1	0.98
Work engagement	4.5	1.0	1	7	0.1	3.1	0.98
Organizational commitment	4.8	1.1	1	7	0.1	3.1	0.98
Turnover intention	1.5	1.0	0	4	0.1	3.1	0.98
Job satisfaction	4.0	1.0	1	7	0.1	3.1	0.98
Perceived stress	3.0	1.0	1	6	0.1	3.1	0.98
Work-life balance	4.0	1.0	1	7	0.1	3.1	0.98
Organizational citizenship behavior	4.5	1.0	1	7	0.1	3.1	0.98
Employee well-being	4.5	1.0	1	7	0.1	3.1	0.98
Job burnout	2.5	1.0	1	6	0.1	3.1	0.98

Variable	Mean	SD	Min	Max	Skewness	Kurtosis	Normality test
Age	34.5	10.2	20	65	0.15	3.2	0.98
Gender	0.5	0.5	0	1	0.0	3.0	0.99
Marital status	0.6	0.5	0	1	0.0	3.0	0.99
Education	12.5	2.5	9	16	0.1	3.1	0.98
Income	1500	500	500	3000	0.2	3.3	0.97
Health status	0.7	0.4	0	1	0.0	3.0	0.99
Stress level	3.5	1.5	1	6	0.1	3.1	0.98
Life satisfaction	4.2	1.2	1	7	0.1	3.1	0.98
Work engagement	4.5	1.0	1	7	0.1	3.1	0.98
Organizational commitment	4.8	1.1	1	7	0.1	3.1	0.98
Turnover intention	1.5	1.0	0	4	0.1	3.1	0.98
Job satisfaction	4.0	1.0	1	7	0.1	3.1	0.98
Perceived stress	3.0	1.0	1	6	0.1	3.1	0.98
Work-life balance	4.0	1.0	1	7	0.1	3.1	0.98
Organizational citizenship behavior	4.5	1.0	1	7	0.1	3.1	0.98
Employee well-being	4.5	1.0	1	7	0.1	3.1	0.98
Job burnout	2.5	1.0	1	6	0.1	3.1	0.98
Work engagement	4.5	1.0	1	7	0.1	3.1	0.98
Organizational commitment	4.8	1.1	1	7	0.1	3.1	0.98
Turnover intention	1.5	1.0	0	4	0.1	3.1	0.98
Job satisfaction	4.0	1.0	1	7	0.1	3.1	0.98
Perceived stress	3.0	1.0	1	6	0.1	3.1	0.98
Work-life balance	4.0	1.0	1	7	0.1	3.1	0.98
Organizational citizenship behavior	4.5	1.0	1	7	0.1	3.1	0.98
Employee well-being	4.5	1.0	1	7	0.1	3.1	0.98
Job burnout	2.5	1.0	1	6	0.1	3.1	0.98

Variable	Mean	SD	Min	Max	Skewness	Kurtosis	Normality test
Age	34.5	10.2	20	65	0.15	3.2	0.98
Gender	1.2	0.4	1	2	0.05	3.0	0.99
Marital status	1.8	0.4	1	2	0.05	3.0	0.99
Education	12.5	2.1	9	16	0.10	3.1	0.97
Income	1500	500	500	3000	0.20	3.3	0.95
Health status	1.5	0.5	1	2	0.05	3.0	0.99
Stress level	2.5	0.8	1	4	0.10	3.1	0.97
Life satisfaction	3.5	0.7	1	5	0.05	3.0	0.99
Work engagement	4.0	0.6	1	5	0.05	3.0	0.99
Organizational commitment	4.2	0.5	1	5	0.05	3.0	0.99
Job satisfaction	3.8	0.6	1	5	0.05	3.0	0.99
Turnover intention	1.0	0.3	1	2	0.05	3.0	0.99
Organizational citizenship behavior	3.0	0.5	1	4	0.05	3.0	0.99
Employee well-being	3.2	0.6	1	4	0.05	3.0	0.99
Work-life balance	3.0	0.5	1	4	0.05	3.0	0.99
Perceived organizational support	3.5	0.6	1	4	0.05	3.0	0.99
Psychological safety	3.8	0.5	1	4	0.05	3.0	0.99
Trust in supervisor	3.5	0.6	1	4	0.05	3.0	0.99
Trust in organization	3.2	0.5	1	4	0.05	3.0	0.99
Organizational justice	3.0	0.5	1	4	0.05	3.0	0.99
Employee voice	3.5	0.6	1	4	0.05	3.0	0.99
Employee silence	1.5	0.4	1	2	0.05	3.0	0.99
Employee turnover	1.0	0.3	1	2	0.05	3.0	0.99
Employee retention	4.0	0.6	1	5	0.05	3.0	0.99
Employee loyalty	4.2	0.5	1	5	0.05	3.0	0.99
Employee engagement	4.0	0.6	1	5	0.05	3.0	0.99
Employee commitment	4.2	0.5	1	5	0.05	3.0	0.99
Employee satisfaction	3.8	0.6	1	5	0.05	3.0	0.99
Employee well-being	3.2	0.6	1	4	0.05	3.0	0.99
Employee work-life balance	3.0	0.5	1	4	0.05	3.0	0.99
Employee perceived organizational support	3.5	0.6	1	4	0.05	3.0	0.99
Employee psychological safety	3.8	0.5	1	4	0.05	3.0	0.99
Employee trust in supervisor	3.5	0.6	1	4	0.05	3.0	0.99
Employee trust in organization	3.2	0.5	1	4	0.05	3.0	0.99
Employee organizational justice	3.0	0.5	1	4	0.05	3.0	0.99
Employee voice	3.5	0.6	1	4	0.05	3.0	0.99
Employee silence	1.5	0.4	1	2	0.05	3.0	0.99
Employee turnover	1.0	0.3	1	2	0.05	3.0	0.99
Employee retention	4.0	0.6	1	5	0.05	3.0	0.99
Employee loyalty	4.2	0.5	1	5	0.05	3.0	0.99
Employee engagement	4.0	0.6	1	5	0.05	3.0	0.99
Employee commitment	4.2	0.5	1	5	0.05	3.0	0.99
Employee satisfaction	3.8	0.6	1	5	0.05	3.0	0.99
Employee well-being	3.2	0.6	1	4	0.05	3.0	0.99
Employee work-life balance	3.0	0.5	1	4	0.05	3.0	0.99
Employee perceived organizational support	3.5	0.6	1	4	0.05	3.0	0.99
Employee psychological safety	3.8	0.5	1	4	0.05	3.0	0.99
Employee trust in supervisor	3.5	0.6	1	4	0.05	3.0	0.99
Employee trust in organization	3.2	0.5	1	4	0.05	3.0	0.99
Employee organizational justice	3.0	0.5	1	4	0.05	3.0	0.99
Employee voice	3.5	0.6	1	4	0.05	3.0	0.99
Employee silence	1.5	0.4	1	2	0.05	3.0	0.99
Employee turnover	1.0						

performance may be related to the crystal size of the sample. By analogy, it is assumed that the relatively poor performance of the IrO_2 -containing samples is similarly due, at least in part, to the lack of discernable crystal structure.

FIG. 4C is a Tafel plot of the oxygen evolution of samples C6 and C8-C10, and illustrates the effect of varying the amount of TiO_2 in solid solutions of $\text{RuO}_2/\text{TiO}_2$. As shown in FIG. 4B, sample C10 (90:10 Ru/Ti atomic ratio) exhibited superior performance to sample C6 (RuO_2 catalyst composition). Sample C9 (70:30 Ru/Ti atomic ratio) exhibited comparable performance to sample C6, whereas sample C7 (50:50 Ru/Ti atomic ratio) exhibited poorer performance in comparison. Thus, it seems that increasing the ratio of Ti in the $\text{RuO}_2/\text{TiO}_2$ solid solution beyond about 70:30 Ru/Ti results in loss of oxygen evolution performance, relative to the RuO_2 catalyst composition.

Tests more representative of cell reversal tolerance in fuel cell operation were then performed in an effort to correlate the ex-situ oxygen evolution performance results of the catalyst composition samples with voltage reversal tolerance in solid polymer electrolyte fuel cells.

A series of solid polymer fuel cells was constructed in order to determine how additional RuO_2 incorporated into the anode in various ways improved tolerance during voltage reversal. A set of anodes was then prepared using some of the

preceding catalyst compositions in various combinations for evaluation in test fuel cells. In these anodes, the catalyst compositions were applied in one or more separate layers in the form of aqueous inks on porous carbon substrates using a screen printing method. The aqueous inks comprised catalyst, ion conducting ionomer, and a binder. The MEAs (membrane electrode assemblies) for these cells employed a conventional cathode having platinum black (that is, unsupported) catalyst applied to a porous carbon substrate, and a conventional perfluorinated solid polymer membrane. The catalyst loadings on the anodes were in the range of 0.2 - 0.3 mg Pt/cm².

The fuel cells prepared included:

- FC1: anode has a single catalyst layer containing composition C1;
- FC2: anode has a single catalyst layer containing composition C2;
- FC3: anode has a single catalyst layer containing composition C3;
- FC4: anode has a single catalyst layer containing composition C4;
- FC5: anode has a single catalyst layer containing composition C5;
- FC6: anode has a single catalyst layer containing composition C6;
- FC2/6: anode has two layers of catalyst, a lower layer adjacent the substrate containing composition C2 and an upper layer containing composition C6.

- FC6/2: anode has two layers of catalyst, a lower layer adjacent the substrate containing composition C6 and an upper layer containing composition C2.
- 5 FC2+6: anode has a single catalyst layer containing a mixture of compositions C2 and C6.

Each cell was conditioned prior to voltage reversal testing by operating it normally at a current density of about 0.5 A/cm^2 and a temperature of approximately 75°C . Humidified hydrogen was used as fuel and humidified air as the oxidant, both at 200 kPa pressure. The stoichiometry of the reactants (that is, the ratio of reactant supplied to reactant consumed in the generation of electricity) was 1.5 and 2 for the hydrogen and oxygen-containing air reactants, respectively. The output cell voltage as a function of current density (polarization data) was then determined. After that, each cell was subjected to a voltage reversal test by flowing humidified nitrogen over the anode (instead of fuel) while forcing 10A current through the cell for 23 minutes using a constant current power supply connected across the fuel cell. (The period of 23 minutes was selected on the basis of results from cell FC2. This time period was significant enough to cause some damage to its conventional anode without causing the extensive damage associated with large increases in the anode potential.)

During the voltage reversal, the cell voltage versus time was recorded. The production of CO_2 and O_2 gases were also monitored by gas chromatography and the equivalent currents consumed to produce these gases were calculated in accordance with the preceding reactions for a fuel starvation condition. Polarization data for each cell was obtained after the reversals to determine the effect of a single reversal episode on cell performance.

Then, each cell was subjected to a second voltage reversal test at a 10 A current. This time, however, the reversal current was interrupted five times during the test period to observe the effect of repeated reversals on the cells. After 5 minutes of operation in reversal, the current was cycled on and off five times (20 seconds off and 10 seconds on) after which the current was left on until a total "on" time of 23 minutes had been reached. Following the second reversal test, polarization measurements of each cell were obtained.

FIG. 5A shows the voltage versus time plots for cells FC1-FC6 during the first voltage reversal period. Cell FC3 had a similar anode to cell FC1 except that cell FC3 additionally contained RuO_2 . Cell FC3 operated at a slightly lower anode potential than cell FC1 during reversal (that is, at a less negative cell voltage). Cell FC4 had a similar anode to cell FC2 except that cell FC4 additionally contained

RuO₂. Cell FC4 operated at a significantly lower anode potential than cell FC2 during reversal. Near the end of the reversal period, the anode potential in cell FC2 rose dramatically. Cell FC5
5 had a similar anode to cell FC4 except that the carbon support had been graphitized. Cell FC5 operated at a significantly lower anode potential than cell FC4 during reversal.

FIG. 5B shows the current consumed in the
10 production of CO₂ versus time plots for cells FC1-FC6 during the first reversal period. Cell FC3 shows less CO₂ production over time than cell FC1. Also, cell FC4 shows less CO₂ production over time than cell FC2. Cell FC5 shows less CO₂ production
15 over time than cell FC4. Cell FC6 containing only the electrolysis catalyst RuO₂ showed a CO₂ production level somewhat greater than cell FC3. (Note that substantially, the current forced through the cells during reversal testing could be
20 accounted for by the sum of the equivalent currents associated with the generation of CO₂ and O₂. Thus, the reaction mechanisms above appear consistent with the test results.)

FIG. 6A shows the voltage versus time plots
25 for cells FC2/6, FC6/2, and FC 2+6 during the first voltage reversal period. These cells have a similar anode to cell FC2 except that they contained additional RuO₂ either in another layer or mixed in the same layer on a different carbon
30 support. FIG. 6B shows the current consumed in the production of CO₂ versus time plots for these

002220"0554450

same cells. These cells operated at somewhat lower anode potentials than cell FC2 and showed somewhat less CO₂ production over time than cell FC2.

5 FIG. 7 shows the voltage versus time plots for the cells during the second voltage reversal test (except for cell FC6 that was not tested). This time, cell FC3 showed the lowest anode potential near the end of the reversal test.

10 The Table below summarizes the results of the polarization testing. In this Table, the voltages were determined at a current density of 800 amps/ft² (860 mA/cm²).

Fuel cell #	Voltage before reversal tests (mV)	ΔV (mV before tests - mV after 1st reversal test)	ΔV (mV before tests - mV after 2nd reversal test)
FC1	616	33	149
FC2	594	120	>394*
FC3	521	27	89
FC4	438	23	64
FC5	590	47	50
FC2/6	272	>72*	>72*
FC6/2	561	37	88
FC2+6	516	30	87

15

* The programmable load was incapable of sustaining 800 amps/ft² (860 mA/cm²) when the voltage across the fuel cell was less than 200 mV and thus the cell voltage was only known to be
20 less than 200 mV at 800 amps/ft² (860 mA/cm²).

002280-05564960

The above examples show that, for a given carbon support, the addition of RuO_2 to the anode results in a reduction in the anode overpotential and in carbon corrosion during voltage reversal and also results in less subsequent performance degradation (comparing cells FC4 and FC5 to FC2, and cell FC3 to FC1). Further, such improvements may be obtained by adding the RuO_2 in a variety of ways. For instance, the RuO_2 may be deposited onto a conventional carbon supported catalyst used in the anode (for example, FC4) or deposited onto another carbon support and added to the anode in a separate catalyst layer (for example, FC6/2) or added to the anode in the same layer as the conventional catalyst (for example, FC2+6).

On the basis of the anode voltages and carbon corrosion observed during the first reversal tests alone, it would appear that graphitized Vulcan furnace black is the preferred choice for a reversal tolerant carbon support, followed by Shawinigan acetylene black, and then the untreated Vulcan furnace black. However, consideration should be given to additional factors in the selection of a preferred carbon support (for example, effects in multiple and/or other voltage reversal scenarios).

A second series of solid polymer fuel cells was constructed in order to evaluate how incorporating various of the prepared catalyst compositions into the anode improved tolerance

during voltage reversal in cells operating on reformat (instead of on pure hydrogen fuel as in the preceding series).

A second set of anodes was thus prepared
5 using various combinations of catalyst
compositions for evaluation in test fuel cells.
In these anodes, the catalyst compositions were
applied by spraying an aqueous ink comprising
catalyst, ion conducting ionomer, and a binder
10 onto porous carbon substrates to a total Pt
loading of about 0.1 mg/cm^2 . The MEAs (membrane
electrode assemblies) for these cells employed a
conventional cathode having carbon-supported
platinum catalyst applied to a porous carbon
15 substrate (Pt supported on Vulcan XC72R; Pt
loading $\approx 0.7 \text{ mg/cm}^2$), and a conventional Nafion[®]
perfluorinated solid polymer membrane.

The fuel cells prepared included:

FCR1: anode has a single catalyst layer
20 containing composition C1;
FCR2: anode has a single catalyst layer
containing composition C2;
FCR3: anode has a single catalyst layer
containing composition C3;
25 FCR1+6: anode has a single catalyst layer
containing a mixture of compositions C1
and C6;
FCR1/6: anode has two layers of catalyst, a
lower layer adjacent the substrate
30 containing composition C1 and an upper
layer containing composition C6;

002250"0564950

5 FCR2+6: anode has a single catalyst layer
containing a mixture of compositions C2
and C6;

FCR1+10: anode has a single catalyst layer
containing a mixture of compositions C1
10 and C10;

FCR1+11: anode has a single catalyst layer
containing a mixture of compositions C1
and C11;

FCR1+13: anode has a single catalyst layer
15 containing a mixture of compositions C1
and C13;

FCR1+14: anode has a single catalyst layer
containing a mixture of compositions C1
and C14.

Each cell was conditioned prior to voltage reversal testing in a manner similar to that of the preceding series of cells. However, after conditioning all the subsequent testing on this second series was done with the fuel and air supplied at 160 kPa pressure and at stoichiometries of 1.2 and 1.5, respectively. Before subjecting the cells to voltage reversal testing, the output cell voltage as a function of current density (polarization data) was determined using reformat instead of humidified hydrogen.

Here, the reformatte comprises 65% hydrogen, 22% CO₂, 13% N₂, 40 parts per million (ppm) CO, saturated with water at 75°C, with an added 4% by volume air (the small amount of air being provided to counteract CO poisoning of the anode catalyst).

Each cell was then subjected to voltage reversal testing in three steps:

- Step 1: 200 mA/cm² current was forced through each cell for 5 minutes while flowing humidified nitrogen (instead of fuel) over the anode. The cells were allowed to recover for 15 minutes at 1A/cm² while operating on hydrogen and air.
- Step 2: The cells were subjected to 200 mA/cm² current pulses while operating on nitrogen and air. The pulse testing consisted of three sets of 30 pulses (10 seconds on/10 seconds off) with similar recovery periods (1 A/cm² while operating on hydrogen and air) for 15 minutes in between sets and overnight after the last set of pulses.
- Step 3: 200 mA/cm² current was forced through the cells until -2V was reached. The polarization tests were then repeated on the cells using reformatte fuel.

A first test was performed using cells FCR3, FCR1+6, FCR1/6, FCR6/1, FCR2+6, and FCR2, to evaluate the effect of incorporating RuO₂ into the anode improved voltage reversal tolerance. The Table below summarizes the results of the

polarization testing before and after steps 2 and 3 in the voltage reversal testing. In this Table, the voltages were determined at a current density of 800 mA/cm².

5

Fuel cell #	Voltage before reversal tests (mV)	ΔV (mV before tests - mV after Step 2)	ΔV (mV before tests - mV after Step 3)
FCR3	504	25	>304*
FCR1+6	518	-6	129
FCR1/6	236	-52	>36*
FCR6/1	556	38	236
FCR2+6	573	184**	**
FCR2	544	237**	**

* The programmable load was incapable of sustaining 800 mA/cm² when the voltage across the fuel cell was less than 200 mV and thus the cell voltage was only known to be less than 200 mV at 800 mA/cm².

** These cells reached -2V during the step 2 of voltage reversal testing at which point voltage reversal testing was halted and polarization data was obtained.

In cell FCR3, the RuO₂ was formed on the same carbon support as the conventional Pt/Ru catalyst,

002250"035E4950

while in cell FCR1+6, RuO₂ and the conventional Pt/Ru catalysts were formed on separate batches of the same carbon support and the two catalysts were then mixed together. Both cells showed similar
5 behavior before reversal testing began and also during the first two voltage reversal testing steps. However, while both cells operated about the same length of time during step 3 (to the -2V voltage cutoff), cell FCR3 degraded significantly
10 more than cell FCR1+6.

Cells FCR1/6 and FCR6/1 had separate RuO₂ catalyst layers adjacent the membrane and adjacent the anode substrate respectively. Cell FCR1/6 showed poor polarization performance initially
15 which improved slightly after step 2. However, cell FCR1/6 was characterized by an exceptionally long electrolysis plateau during step 3 and thus appeared very resistant to degradation during voltage reversal. Cell FCR6/1 on the other hand
20 showed good polarization performance initially but degraded substantially after step 3.

As illustrated in the Table above, cells FCR2 (employing Vulcan based carbon supported Pt/Ru catalyst) and FCR2+6 (employing an admixture of
25 Vulcan based carbon supported Pt/Ru catalyst and Shawinigan based carbon supported RuO₂ catalyst) showed good initial polarization performance. The catalyst admixture of cell FCR2+6 appeared to help reduce the degradation associated with voltage
30 reversal testing. However, both cells degraded significantly during voltage reversal testing to

002280"0654960

the point where the -2V voltage cutoff was reached before step 3 could be started.

In this first test, the admixture FCR1+6 showed the best polarization results after the voltage reversal testing. All of the cells with added RuO₂ (FCR3, FCR1+6, FCR1/6, FCR6/1 and FCR2+6), however, show improved voltage reversal tolerance over cell FCR2.

A second test was performed using cells FCR1, FCR1+6, FCR1+10 and FCR1+11, to evaluate the effect on voltage reversal tolerance of other oxides as mixtures and/or solid solutions with RuO₂ in the present anode structures.

FIG. 8 shows the voltage versus time plots for cells FCR1, FCR1+6, FCR1+10, and FCR1+11 during step 3 of the voltage reversal testing. As shown in FIG. 8, cell FCR1 (incorporating conventional carbon supported Pt/Ru catalyst) degraded almost immediately (within about 15 seconds). FCR1+6 showed significant improvement over FCR1, but also degraded within 5 minutes. FCR1+10 (incorporating an admixture of carbon supported Pt/Ru catalyst and carbon supported RuO₂/TiO₂ catalyst) showed dramatic improvement over FCR1 and FCR1+6, and FCR1+11 (incorporating an admixture of carbon supported Pt/Ru catalyst and carbon supported RuO₂/IrO₂ catalyst) showed the best performance of the cells tested.

As illustrated in FIG. 8, catalyst compositions comprising RuO₂ showed marked increases in voltage reversal tolerance relative

002230-0564960

A third test was performed using cells FCR1+6, FCR1+13 and FCR1+14, to evaluate the effect of crystal size in RuO₂ catalyst compositions on voltage reversal tolerance.

FIG. 9 shows the voltage versus time plots for cells FCR1+6, FCR1+13 and FCR1+14, during steps 1 and 2 of the voltage reversal testing. As illustrated in FIG. 9, all cells tested showed good initial polarization performance during step 1 (between 0 and 1000 seconds). FCR1+13 (RuO₂ crystal size, 2.2 nm) degraded significantly during voltage reversal testing to the point where the -2V voltage cutoff was reached before the third set of current pulses could be completed. FCR1+6 (RuO₂ crystal size, 6.5 nm) demonstrated a marked increase in voltage reversal tolerance compared to FCR1+13, although some degradation was observed, particularly during the third current pulse set. FCR1+14 (average RuO₂ crystal size,

13.0 nm), however, demonstrated the best voltage reversal tolerance, with no significant degradation during steps 2 and 3.

As illustrated in FIG. 9, it appears that
5 there is a correlation between voltage reversal tolerance and RuO₂ crystal size in the RuO₂ catalyst compositions, with the larger crystals tested having the greatest voltage reversal tolerance. This data also correlates with the ex-
10 situ oxygen evolution data.

While the present anodes have been described for use in solid polymer electrolyte fuel cells, it is anticipated that they would be useful in other fuel cells, as well. In this regard, "fuel
15 cells" refers to any fuel cell having an operating temperature below about 250°C. The present anodes are preferred for acid electrolyte fuel cells, which are fuel cells comprising a liquid or solid acid electrolyte, such as phosphoric acid, solid
20 polymer electrolyte, and direct methanol fuel cells, for example. The present anodes are particularly preferred for solid polymer electrolyte fuel cells.

While particular elements, embodiments and
25 applications of the present invention have been shown and described, it will be understood, of course, that the invention is not limited thereto since modifications may be made by those skilled in the art without departing from the scope of the
30 present disclosure, particularly in light of the foregoing teachings.

002240"0564360

What is claimed is:

1. An anode for use in a fuel cell having improved tolerance to voltage reversal, said anode comprising a first catalyst composition for electrochemically oxidizing a fuel directed to said anode and a second catalyst composition for evolving oxygen from water.

2. The anode of claim 1 wherein said fuel cell is an acid electrolyte fuel cell.

3. The anode of claim 1 wherein said fuel cell is a solid polymer electrolyte fuel cell.

4. The anode of claim 3 wherein said first catalyst composition is selected from the group consisting of precious metals, transition metals, oxides of precious metals and transition metals, alloys of precious metals and transition metals, and mixtures of precious metals and transition metals.

5. The anode of claim 3 wherein said first catalyst composition is selected from the group consisting of precious metals, alloys of precious metals, mixtures of precious metals, precious metals alloyed with transition metals, and mixtures of precious metals and transition metal oxides.

6. The anode of claim 3 wherein said first catalyst composition comprises a platinum-

containing compound selected from the group
consisting of platinum and an alloy of platinum and
5 ruthenium.

7. The anode of claim 3 wherein said second
catalyst composition comprises a metal oxide
selected from the group consisting of precious
metal oxides, mixtures of precious metal oxides,
5 solid solutions of precious metal oxides, mixtures
of precious metal oxides and valve metal oxides,
and solid solutions of precious metal oxides and
valve metal oxides.

8. The anode of claim 7 wherein said metal
oxide comprises a precious metal oxide selected
from the group consisting of RuO_x , IrO_x , and solid
solutions of RuO_x and IrO_x , wherein x is greater
5 than 1.

9. The anode of claim 8 wherein x is about
2.

10. The anode of claim 7 wherein said metal
oxide is selected from the group consisting of RuO_2
and solid solutions of RuO_2 and IrO_2 .

11. The anode of claim 10 wherein said metal
oxide comprises RuO_2 .

12. The anode of claim 10 wherein said metal
oxide comprises a solid solution of RuO_2 and IrO_2
having iridium present in an atomic ratio of
ruthenium to iridium of no greater than 90:10.

002220"0334950

5

V

Y

r

Y

i

20. The anode of claim 7 wherein said first catalyst composition comprises a platinum-containing compound selected from the group consisting of platinum and an alloy of platinum and ruthenium.

21. The anode of claim 9 wherein said first catalyst composition comprises a platinum-containing compound selected from the group consisting of platinum and an alloy of platinum and ruthenium.

22. The anode of claim 13 wherein said first catalyst composition comprises a platinum-containing compound selected from the group consisting of platinum and an alloy of platinum and ruthenium.

23. The anode of claim 15 wherein said first catalyst composition comprises a platinum-containing compound selected from the group consisting of platinum and an alloy of platinum and ruthenium.

24. The anode of claim 3 wherein said first catalyst composition is supported on a first electrically conductive particulate support.

25. The anode of claim 24 wherein said first catalyst composition is supported on a first carbon support.

002220-035450

27. The anode of claim 26 wherein said second catalyst composition is supported on a second carbon support.

29. The anode of claim 26 wherein said second catalyst composition is supported on a valve metal oxide support.

31. The anode of claim 3 wherein said first and second catalyst compositions are incorporated in a common layer in said anode.

33. The anode of claim 3 wherein said fuel stream comprises gaseous hydrogen.

5

second catalyst composition is deposited on an electrically conductive particulate support.

second catalyst composition is deposited on a carbon support.

37. The method of claim 36 wherein said first catalyst composition and said second catalyst composition are deposited on said carbon support.

5

5

p

 t

○

Abstract

In a solid polymer fuel cell series, various circumstances can result in the fuel cell being driven into voltage reversal. For instance, cell voltage reversal can occur if that cell receives an inadequate supply of fuel (for example, fuel starvation). In order to pass current during fuel starvation, reactions other than fuel oxidation may take place at the fuel cell anode, including water electrolysis and oxidation of anode components. The latter may result in significant degradation of the anode. Such fuel cells can be made more tolerant to cell reversal by promoting water electrolysis over anode component oxidation at the anode. This can be accomplished by incorporating a catalyst composition at the anode to promote the water electrolysis reaction, in addition to the typical anode electrocatalyst for promoting fuel oxidation.

002280" 0554560




FIG. 1





FIG. 2



0964350 032200
FIG. 3A



FIG. 3B




FIG. 4A

09643550 002200







FIG. 4C

09643590-092200

FIG. 5A

**FIG. 5B**

**FIG. 6A**

**FIG. 6B**

002280" 05564960






FIG. 7



091543 0312200
FIG. 8

FIG. 9



Variable	Mean	SD	Min	Max
Age (years)	34.5	10.2	18	65
Gender (male/female)	15/15	0	0	30
Education (years)	12.5	1.5	8	16
Occupation (white/blue)	10/10	0	0	20
Marital status (married/single)	12/8	0	0	20
Income (€1000/month)	1.5	0.5	0.5	2.5
Health status (good/poor)	18/2	0	0	20
Smoking status (smoker/non-smoker)	10/10	0	0	20
Alcohol consumption (g/day)	10	10	0	50
Physical activity (hours/week)	2.5	1.5	0	6
Stress level (low/high)	10/10	0	0	20
Sleep quality (good/poor)	12/8	0	0	20
Dietary intake (vegetarian/non-vegetarian)	10/10	0	0	20
Family size (number of children)	1.5	0.5	0	3
Work hours (hours/week)	35	5	20	40
Comorbidity (yes/no)	5/15	0	0	20
Medication use (yes/no)	5/15	0	0	20
Health insurance (private/public)	10/10	0	0	20
Urban/rural residence	10/10	0	0	20
Transportation (car/bike/public)	10/10	0	0	20
Language spoken at home (German/Other)	10/10	0	0	20
Religious affiliation (Christian/Other)	10/10	0	0	20
Political orientation (left/right)	10/10	0	0	20
Volunteer work (hours/month)	2	2	0	6
Life satisfaction (1-5)	3.5	0.5	1	5
Perceived stress (1-5)	2.5	0.5	1	5
Health-related quality of life (SF-36)	50	10	20	100